AMENDMENT AND PRESENTATION OF CLAIMS

Please replace all prior claims in the present application with the following claims, in which claims 1-13 are currently amended.

1. (Currently Amended) A method ~~Method~~ for monitoring ~~the~~ stability of ~~the~~ a carrier frequency (ω_i) of identical transmitted signals ($s_i(t)$) of several transmitters ($S_1,\ldots,S_i,\ldots,S_n$) of a single-frequency network ~~by~~ comprising:

receiving, by a receiver device (E) positioned within the transmission range of the single-frequency network, a signal ($e_i(t)$) associated with a transmitted signal ($s_i(t)$) of a transmitter (S_i) and a reference signal ($e_0(t)$) of a reference transmitter (S_0); and

evaluating ~~the~~ a phase position of ~~a~~ the received signal ($e_i(t)$) associated with ~~a~~ the transmitted signal ($s_i(t)$) of ~~a~~ the transmitter (S_i) with reference to ~~a~~ the received signal ($e_0(t)$) of ~~a~~ the reference transmitter (S_0)~~, both of which are received by a receiver device (E) positioned within the transmission range of the single frequency network~~.

2. (Currently Amended) A method ~~Method~~ according to claim 1, ~~characterised by~~ further comprising:

~~a calculation (S70) of~~ calculating a carrier-frequency displacement ($\Delta\omega_i$) of a carrier frequency (ω_i) of a transmitter (S_i) relative to a reference carrier frequency (ω_0) of the reference transmitter (S_0) from a phase-displacement difference ($\Delta\Delta\Theta_i(t_{B2}-t_{B1})$) caused by the carrier-frequency displacement ($\Delta\omega_i$) of this transmitter between a phase displacement ($\Delta\Theta_i(t_{B2})$) at least at one second observation time (t_{B2}) and a phase displacement ($\Delta\Theta_i(t_{B1})$) at a first observation time (t_{B1}) of a received signal ($e_i(t)$) of this transmitter (S_i) associated with the transmitted signal

($s_i(t)$) relative to a received signal ($e_0(t)$) of the reference transmitter (S_0) associated with the transmitted signal ($s_0(t)$).

3. (Currently Amended) A method ~~Method~~ for monitoring the stability of the carrier frequency according to claim 2, ~~characterised in that the calculation (S70) of the carrier frequency displacement ($\Delta\omega_i$) of the carrier frequency (ω_i) of the transmitter (S_i) relative to the carrier frequency (ω_0) of the reference transmitter (S_0) from the phase displacement difference ($\Delta\Delta\Theta_i(t_{B2}-t_{B1})$) is preceded by the procedural stages listed below~~ wherein said calculating includes:

~~– determination (S10) of~~ determining a transmission function ($H_{SFN}(f)$) of the transmission channel from the transmitters ($S_1,\ldots,S_i,\ldots,S_n$) to the receiver device (E),

~~– calculation (S20) of~~ calculating a characteristic of a complex, time-discrete, summated impulse response ($h_{SFN1}(t)$) at the first observation time (t_{B1}) and a characteristic of a complex, time-discrete, summated impulse response ($h_{SFN2}(t)$) at the second observation time (t_{B2}) of the transmission channel respectively from the transmission function ($H_{SFN}(f)$) of the transmission channel,

~~– masking (S30) of~~ masking a characteristic of a complex impulse response ($h_{SFN1i}(t)$) at the first observation time (t_{B1}) and of a characteristic of a complex impulse response ($h_{SFN2i}(t)$) at the second observation time (t_{B2}) for every transmitter (S_i) of the single-frequency network respectively from the characteristic of the complex, summated impulse response ($h_{SFN1}(t)$) at the first observation time (t_{B1}) and from the characteristic of the complex, summated impulse response ($h_{SFN2}(t)$) at the second observation time (t_{B2}),

~~– determination (S40) of~~ determining a phase characteristic ($\arg(h_{SFN1i}(t))$) of the complex impulse response ($h_{SFN1i}(t)$) at the first observation time (t_{B1}) and of a phase characteristic

($\arg(h_{SFN2i}(t))$ of the complex impulse response ($h_{SFN2}(t)$) at the second observation time (t_{B2}) for every transmitter (S_i) of the single-frequency network, and

~~calculation (S50) of~~ calculating the phase-displacement difference ($\Delta\Delta\Theta_i(t_{B2}-t_{B1})$) between a phase displacement ($\Delta\Theta_i(t_{B2})$) at the second observation time (t_{B2}) and a phase displacement ($\Delta\Theta_i(t_{B1})$) at the first observation time (t_{B1}) by subtraction of a phase characteristic ($\arg(h_{SFN1i}(t))$) of the complex impulse response ($\arg(h_{SFN1i}(t))$ at the first observation time (t_{B1}) from a phase characteristic ($\arg(h_{SFN2i}(t))$) of the complex impulse response ($h_{SFN1i}(t)$) at the second observation time (t_{B2}) of the respective transmitter (S_i).

4. (Currently Amended) A method ~~Method~~ for monitoring the stability of the carrier frequency according to claim 3, ~~characterised by~~ further comprising:

[[-]] increasing ~~(S60)~~ the phase-displacement difference ($\Delta\Delta\Theta_i(t_{B2}-t_{B1})$) by the factor $2*\pi$ in the case of a decrease in the phase-displacement difference ($\Delta\Delta\Theta_i(t_{B2}-t_{B1})$) to the value $-\pi$ or below and

[[-]] reducing ~~(S65)~~ the phase-displacement difference ($\Delta\Delta\Theta_i(t_{B2}-t_{B1})$) by the factor $-2*\pi$ in the case of an increase in the phase-displacement difference ($\Delta\Delta\Theta_i(t_{B2}-t_{B1})$) above the value π.

5. (Currently Amended) A method ~~Method~~ for monitoring the stability of the carrier frequency according to claim 3 ~~or 4~~, ~~characterised in that~~ further comprising:

determining, in the case of digital terrestrial TV, the transmission function of the transmission channel from the transmitters ($S_1,\ldots,S_i,\ldots,S_n$) to the receiver device (E) ~~is determined~~ from the DVB-T symbols of scattered pilot carriers of received signals ($e_i(t)$) of the transmitters ($S_1,\ldots,S_i,\ldots,S_n$) modulated according to the orthogonal-frequency-division-multiplexing (OFDM) method.

6. (Currently Amended) A method ~~Method~~ for monitoring the stability of the carrier frequency according to claim 3, ~~characterised in that~~ wherein:

~~the calculation (S20) of a~~ said calculating the characteristic of a complex, time-discrete, summated impulse response $h_{SFN1/2}(t)$ at the discrete first observation time t_{B1} of the transmission channel is derived from the transmission function $H_{SFN}(f)$ of the transmission channel using the Fourier transform according to the formula:

$$h_{SFN1/2}(t) = \sum_{k=0}^{N_F-1} H_{SFN}(k) * e^{j2\pi kt/N_F}$$

wherein

$H_{SFN}(f)$ denotes the transmission function or respectively the frequency response of the transmission channel,

N_F denotes the number of sampling values for the discrete Fourier transform,

k denotes the discrete frequency values,

t denotes the sampling times of the time-discrete, summated impulse response of the transmission channel and

1/2 denotes the index for the observation time t_{B1} or respectively t_{B2}.

7. (Currently Amended) A method ~~Method~~ for monitoring the stability of the carrier frequency according to claim 6, ~~characterised in that~~ wherein:

~~the calculation (S20) of a~~ said calculating the phase-displacement difference ($\Delta\Delta\Theta_i(t_{B2}-t_{B1})$) for each transmitter S_i of the single-frequency network is derived according to the formula:

$$\Delta\Delta\Theta_i(t_{B2}-t_{B1}) = \arg(h_{SFN2i}(t)) - \arg(h_{SFN1i}(t))$$

wherein

i denotes the index for the transmitter S_i

$arg(h_{SFN2i}(t))$ denotes the phase characteristic of the complex impulse response $h_{SFN2i}(t)$ at the observation time t_{B2} of the transmitter S_i and

$arg(h_{SFN1i}(t))$ denotes the phase characteristic of the complex impulse response $h_{SFN1i}(t)$ at the observation time t_{B1} of the transmitter S_i.

8. (Currently Amended) A method ~~Method~~ for monitoring the stability of the carrier frequency according to claim 7, ~~characterised in that~~ wherein:

~~the calculation (S20) of a~~ said calculating the carrier-frequency displacement $\Delta\omega_i$ of the transmitter S_i relative to the carrier frequency ω_0 of the reference transmitter of the single-frequency network is derived according to the formula:

$$\Delta\omega_I = \Delta\Delta\Theta_i(t_{B2}-t_{B1})/(t_{B2}-t_{B1})$$

wherein

i denotes the index for the transmitter S_i,

$\Delta\Delta\Theta_i(t_{B2}-t_{B1})$ denotes the phase position difference $\Delta\Delta\Theta_i(t_{B2}-t_{B1})$ for the transmitter S_i of the single-frequency network and

t_{B1}, t_{B2} denote the observation times.

9. (Currently Amended) A method ~~Method~~ for monitoring the stability of the carrier frequency according to claim 8, ~~characterised in that to allow an unambiguous identification of the permanent carrier-frequency displacement $\Delta\omega_i$ of the transmitter S_i in the single-frequency network relative to the carrier frequency ω_0 of the reference transmitter S_0 at several observation times t_{Bj}, the~~ further comprising performing the following ~~procedural stages are implemented~~ steps repeatedly:

~~calculation (S20) of~~ calculating the characteristic of the complex, time-discrete, summated impulse response $h_{SFNj}(t)$ and $(h_{SFN(j+1)}(t)$ at the observation times t_{Bj} and $t_{B(j+1)}$,

~~masking (S30) of~~ masking the characteristic of the complex impulse response $h_{SFNji}(t)$ and $h_{SFN(j+1)i}(t)$ at the observation times t_{Bj} and $t_{B(j+1)}$ for every transmitter S_i of the single-frequency network,

~~determination (S40) of~~ determining the phase characteristics $\arg(h_{SFNji}(t)$ and $\arg(h_{SFN(j+1)i}(t))$ of the complex impulse responses $h_{SFNji}(t)$ and $h_{SFN(j+1)i}(t))$ at the observation times t_{Bj} and $t_{B(j+1)}$,

~~calculation (S50) of~~ calculating the phase-displacement difference $(\Delta\Delta\Theta_i(t_{B(j+1)}-t_{Bj}))$ between the phase displacement $\Delta\Theta_i(t_{B(j+1)})$ at the observation time $t_{B(j+1)}$ and the phase displacement $\Delta\Theta_i(t_{Bj})$ at the observation time t_{Bj} for every transmitter S_i of the single-frequency network,

[[-]] increasing ~~(S60)~~ the phase-displacement difference $\Delta\Delta\Theta_i(t_{B(j+1)}-t_{Bj})$ by the factor $2*\pi$ in the case of a decrease in the phase-displacement difference $(\Delta\Delta\Theta_i(t_{B(j+1)}-t_{Bj}))$ to the value $-\pi$ or below,

[[-]] reducing ~~(S65)~~ the phase-displacement difference $(\Delta\Delta\Theta_i(t_{B(j+1)}-t_{Bj}))$ by the factor $2*\pi$ in the case of an increase in the phase-displacement difference $\Delta\Delta\Theta_i(t_{B(j+1)}-t_{Bj})$ above the value π and

~~calculation (S70) of~~ calculating the carrier-frequency displacement $\Delta\omega_{ij}$ of the transmitter S_i relative to the carrier frequency ω_0 of the reference transmitter of the single-frequency network at several observation times t_{Bj}; and ~~that following this,~~

~~an~~ averaging ~~(S80) of~~ all carrier-frequency displacements $\Delta\omega_{ij}$ of every transmitter S_i relative to the carrier frequency ω_0 of the reference transmitter S_0 of the single-frequency network calculated respectively in procedural stage (S70), is implemented at the observation times t_{Bj}.

10. (Currently Amended) A method ~~Method~~ for monitoring the stability of the carrier frequency according to claim 9, ~~characterised in that the~~ wherein said averaging ~~(S80) of~~ all carrier-frequency displacements $\Delta\omega_{ij}$ of every transmitter S_i relative to the carrier frequency ω_0 of a reference transmitter S_0 of the single-frequency network calculated in procedural stage (S70), is implemented using a recursive method.

11. (Currently Amended) A device ~~Device~~ for monitoring the stability of the carrier frequency (ω_i) of identical transmitted signals $s_i(t)$ of several transmitters ($S_1,\ldots,S_i,\ldots,S_n$) of a single-frequency network comprising:

[[-]] a receiver device ~~(E)~~,

[[-]] a unit ~~(11)~~ for determining a transmission function $H_{SFN}(f)$ of a transmission channel of several transmitters ($S_1,\ldots,S_i,\ldots,S_n$) of the single-frequency network to the receiver device ~~(E)~~ disposed within the transmission range of the single-frequency network,

[[-]] a unit ~~(12)~~ for implementing an inverse Fourier transform,

[[-]] a unit ~~(13)~~ for masking a impulse response ($h_{SFNi}(t)$) for every transmitter (S_i) from the summated impulse response ($h_{SFN}(t)$),

[[-]] a unit ~~(14)~~ for determining the phase characteristic ($\arg(h_{SFNi}(t))$) of the impulse response ($h_{SFNi}(t)$) for every transmitter (S_i),

[[-]] a unit ~~(15)~~ for calculating the phase-displacement difference ($\Delta\Delta\Theta_i(t_{B(j+1)}-t_{Bj})$) of the phase displacement ($\Delta\Theta_i$) of a transmitter (S_i) relative to a reference transmitter (S_0) at least at

two different times (($t_{B1,}$-t_{Bj+1})) and the carrier-frequency displacement ($\Delta\omega_i$) of every transmitter (S_i) relative to the carrier frequency (ω_0) of the reference transmitter (S_0), and

[[-]] a unit ~~(2)~~ for presenting the calculated carrier-frequency displacement ($\Delta\omega_i$) of every transmitter (S_i) relative to the carrier frequency (ω_0) of the reference transmitter (S_0) of the single-frequency network.

12. (Currently Amended) A device ~~Device~~ for monitoring the stability of the carrier wave (ω_i) of identical transmitted signals $s_i(t)$ of several transmitters (S_1,...,S_i,...,S_n) of a single-frequency network comprising:

[[-]] a receiver device ~~(E)~~,

[[-]] a unit ~~(16)~~ for determining a transmission function ($H_{SFN}(f)$) from pilot carriers of the received signal ($e_i(t)$),

[[-]] a unit ~~(13)~~ for masking a impulse response ($h_{SFNi}(t)$) for every transmitter (S_i) from the summated impulse response ($h_{SFN}(t)$),

[[-]] a unit ~~(14)~~ for determining the phase characteristic ($\arg(h_{SFNi}(t))$ of the impulse response ($h_{SFNi}(t)$) for every transmitter (S_i),

[[-]] a unit ~~(15)~~ for calculating the phase-displacement difference ($\Delta\Delta\Theta_i(t_{B(j+1)}$-$t_{Bj})$) of the phase displacement $\Delta\Theta_i$ of a transmitter (S_i) relative to a reference transmitter (S_0) at least at two different times (t_{Bj}-$t_{B(j+1)}$) and the carrier-frequency displacement ($\Delta\omega_i$) of every transmitter relative to the carrier frequency (ω_0) of the reference transmitter (S_0), and

[[-]] a unit ~~(2)~~ for presenting the calculated carrier-frequency displacement ($\Delta\omega_i$) of every transmitter (S_i) relative to the carrier frequency (ω_0) of the reference transmitter (S_0) of the single-frequency network.

13. (Currently Amended) A device ~~Device~~ for monitoring the stability of the carrier frequency according to claim 11 ~~or 12~~, ~~characterised in that~~ wherein:

the unit ~~(2)~~ for presenting the calculated carrier-frequency displacement ($\Delta\omega_i$) of every transmitter (S_i) relative to the carrier frequency (ω_0) of the reference transmitter (S_0) comprises a tabular and/or graphic display device.